

marantz®



SR5008

NETWORK AV RECEIVER



green standby
eco friendly

HDMI

HDMI 6+1 In
1 Out

4K HD
VIDEO

PC AUDIO
STREAMING

Spotify



The latest current feedback topology and Marantz own HDAMs are also central to the SR5008. These technologies guarantee both power and detail in your surround sound experience. It also has the networking facilities for gapless HD audio streaming from PC and Android as well as Internet radio, online services and AirPlay from your iPhone, iPad or iPod. And, it includes decoders for standard audio as well as for Dolby TrueHD and DTS-HD Master Audio.

The SR5008 also supports Apple lossless, Gapless, FLAC HD 192/24 so you get all the metadata you want. It comes with no less than six HDMI inputs of which one is on the front – making it immediately ready for 3D /4k video and ARC (Audio Return Channel) from ARC-compatible TV sets. Lower resolution video can be up-scaled to 4k too. It easily handles the most demanding of scenes in action films, as well as offering excellent-quality music playback - thanks to the latest Marantz audio technologies and 180W from the 7 amplifiers. Everything sounds clear, detailed, and alive with this set.

To finish off, the SR5008 comes with a whole range of convenience features such as: Setup Assistant, “auto calibration” with Audyssey MultiEQ XT and Dynamic Volume Control; “Multi-Room” with multi-source flexibility; and “video-off” mode to ensure that you enjoy your music and movies in true dynamic Marantz style. It also has the specially developed Marantz Remote App for iPhone and Android devices. All of which makes the SR5008 a true combination of style, power and ease.

Main Features

- 7ch discrete power amplifier, 180 W per channel
- Current Feedback circuitry with Marantz HDAM
- DLNA1.5 Network audio streaming and Internet radio
- MP3, WAV, AAC, FLAC, WMA, Lossless, FLAC192/24 (HD)
- Gapless Playback
- Spotify*, Flickr, Internet Radio support
- Apple AirPlay and Windows 8/RT compatible
- Audyssey MultEQ XT, Dynamic EQ and Dynamic Volume
- 6+1 in / 1 out HDMI (3D/ARC/CEC/4K)
- Full 4k compatibility – Scaling – Pass through – GUI overlay
- Analogue & HDMI Upconversion to 4k
- Multilingual Setup Assistant and Audyssey calibration makes hook up an easy task
- Multi room/Multi source
- New Marantz Remote App for iOS and Android devices

EAN

EU	SR5008/N1B	4951035050743	Black
	SR5008/N1SG	4951035050736	Silver-Gold
UK	SR5008/T1B	4951035050743	Black
	SR5008/T1SG	4951035050736	Silver-Gold

www.marantz.eu



because music matters

SR5008

NETWORK AV RECEIVER



FEATURES	SR5008
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify*	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet	•
OTHERS	
Bluetooth audio via RX101	optional
Current Feedback Technology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Auto speaker setup by microphone	Audyssey MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion CVBS > HDMI; Comp > HDMI	•
Analogue to HDMI scaling	up to 4k
HDMI to HDMI scaling	up to 4k
Video processing	•
Picture adjust / Noise reduction	• / •
HDMI path through on stand-by	•
4k video pass through	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Variable cross over	•
Optimized Bass Redirection	•
Multiroom zones	1
Zone2 output from 2-channel digital PCM sources (coaxial, optical, HDMI, network)	*

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	2+1 / 1
Component In / Out	2 / 1
HDMI In / Out	6+1 / 1
AUDIO	
Analogue In / Out	4+1 / 0
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out / Main In	• (7.2) / -
Subwoofer Out	2
Zone Preout	Zone2
7.1 multichannel input	•
OTHER	
M-XPort for RX101	•
Speaker A / B	* (assignable)
Height Speaker Terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	• / •
Multi-Room Speaker Terminal	* (assignable)
Marantz remote bus	•
IR Flasher In	•
Network: (IP-control / update)	• / •
RS232C (control / update)	• / •
USB firmware update	•
DC Triggers	•
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	• / • / - / • / • / •
USB Audio / Made for iPod / Works with iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	7
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	180 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	140 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	100 W
70% Guarantee	•
Audio Signal to Noise Ratio	100 dB
FM Tuner	•
GENERAL	
Available colors: Black / Silver-Gold	• / •
System Remote Control	RC021SR
Power Consumption	650 W
Standby Power Consumption	0.2 W (Standby) 0.5 W (CEC Standby) 2.7 W (Network Standby)
Maximum Dimensions (W x D x H) in mm	440 x 335 x 161
Weight in kg	10.1

* not available in all countries

Design and specifications are subject to change by Marantz without notice.