

marantz®



SR6008 AV RECEIVER



green standby
eco friendly

HDAM

dts
Neo:X | 7.1

HDMI 6+1 in
2 out

4K HD
VIDEO

PC AUDIO
STREAMING

Spotify®

AirPlay

Windows 8
Windows RT
Compatible

Just as you would expect from any Marantz AV receiver, the SR6008 pays extra special attention to audio quality, and it creates a highly immersive and richly detailed surround sound experience. Moreover, with the latest current feedback topology and the Marantz own-developed high-definition HDAMs, the SR6008 has both the power and the finesse to astonish and astound.

Not surprisingly, it has the same DLNA networking facilities for HD gapless audio streaming as its big brother, the SR7008, as well as the same Android integration, Spotify Service, Internet radio, and AirPlay from iTunes or any iDevice. It has a highly convenient HDMI input on the front, and two HDMI outs on the rear for simultaneous output. And another, new HDMI output for multiroom use.

Also like its brother, it has Audyssey DSX and DTS Neo:X 7.1 processing, an iPod-digital-compatible USB input and a Phono MM input for vinyl fans. But it's not all about versatility, the SR6008 is also powerful: 185 W for each of its seven channels to be exact. And, because the digital audio signal (up to Dolby TrueHD and DTS-HD) is fed via one of the six 3D 4k video-supporting HDMI inputs, the resulting audio quality is utterly breathtaking. In addition, calibration and optimisation are also quick and easy with the Audyssey MultEQ XT Pro, Setup Assistant and Graphic User Interface overlaid on the picture. Pure enjoyment has never been easier.

Main Features

- 7ch discrete power amplifier, 185 W per channel
- Current Feedback circuitry with Marantz HDAM
- DLNA1.5 Network audio streaming and Internet radio
- MP3, WAV, AAC, FLAC, WMA, Lossless, FLAC192/24 (HD)
- Gapless Playback
- Spotify*, Flickr, Internet Radio support
- Apple AirPlay and Windows 8/RT compatible
- Audyssey MultEQ XT, Dynamic EQ and Dynamic Volume
- DTS Neo:X (up to 7.1) and Audyssey DSX Processing
- 6+1in HDMI (3D/ARC/CEC/4K), HDMI output for Zone2
- Full 4k compatibility – Scaling – Pass through – GUI overlay
- Analogue & HDMI Upconversion to 4k
- InstaPrevue, to preview HDMI input sources on screen
- Multilingual Setup Assistant and Audyssey calibration makes hook up an easy task
- Multi room/Multi source
- Zone2 output from 2-channel digital PCM sources (coaxial, optical, HDMI, network)
- 7.2 Preout, Phono MM amplifier
- New Marantz Remote App for iOS and Android devices

EAN

EU	SR6008/N1B	4951035050712	Black
	SR6008/N1SG	4951035050705	Silver-Gold
UK	SR6008/T1B	4951035050712	Black
	SR6008/T1SG	4951035050705	Silver-Gold

www.marantz.eu



because music matters



marantz®

SR6008 AV RECEIVER



FEATURES SR6008

MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Audyssey DSX	•
DTS Neo:X	* (up to 7.1)
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•

NETWORK

DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify*	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet	•

OTHERS

Bluetooth audio via RX101	optional
Current Feedback Technology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Auto speaker setup by microphone	Audyssey MultEQ XT (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion CVBS > HDMI; Comp > HDMI	•
Analogue to HDMI scaling	up to 4k
HDMI to HDMI scaling	up to 4k
HDMI InstaPrevue	•
Videoprocessing	•
Picture adjust / Noise reduction	• / •
HDMI path though on stand-by	•
4k video pass through	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Variable cross over	•
Optimized Bass Redirection	•
Multiroom zones	1 (incl. HDMI)
Zone output from 2-channel digital PCM sources (coaxial, optical, HDMI, network)	•

INPUTS/OUTPUTS

VIDEO

Composite In / Out	3+1 / 2
Component In / Out	2 / 1
HDMI In / Out	6+1 / 2 (Main/Zone2)

AUDIO

Analogue In / Out	6 / 1
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out	• (7.2)
Subwoofer Out	2
Zone Preout	Zone2
7.1 multichannel input	•
Phono MM	•

OTHERS

M-XPort for RX101	•
Speaker A / B	•
Height Speaker Terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	•
Wide Speaker Terminal	•
Multi-Room Speaker Terminal	• (assignable)
Marantz remote bus	•
IR Flasher In	•
Network: (IP-control / update)	• / •
RS232C (control / update)	• / •
USB firmware update	•
DC Triggers	•
Front Inputs: Audio / Composite / HDMI / USB	• / • / • / •
USB Audio / Made for iPod / Works with iPhone	• / • / •

SPECIFICATIONS

Number of poweramps	7
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	185 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	150 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	110 W
70% Guarantee	•
Audio Signal to Noise Ratio	100 dB
FM Tuner	•

GENERAL

Available colors: Black / Silver-Gold	• / •
System Remote Control	RC022SR
Metal Front Panel	•
Power Consumption	650 W
Standby Power Consumption	0.2 W (Standby) 0.5 W (CEC Standby) 2.7 W (Network Standby)
Maximum Dimensions (W x D x H) in mm	440 x 389 x 161
Weight in kg	11.2

* not available in all countries

Design and specifications are subject to change by Marantz without notice.